




# TRANSFER OIL

Pure Fluid Attitude



## Male NPT | Female NPT

---



| Part no.              | Description                   | Side A | Side B | ID  | HEX         | L  | MAWP |
|-----------------------|-------------------------------|--------|--------|-----|-------------|----|------|
| D9DMC<br>01FC02<br>01 | 1/16 M-NPT F-NPT 1/8 15k 316D | 1/16   | 1/8    | 3.2 | 5/8   16    | 25 | 15k  |
| D9DMC<br>01FC04<br>01 | 1/16 M-NPT F-NPT 1/4 15k 316D | 1/16   | 1/4    | 3.2 | 3/4   19    | 28 | 15k  |
| D9DMC<br>02FC01<br>01 | 1/8 M-NPT F-NPT 1/16 15k 316D | 1/8    | 1/16   | 4   | 1/2   13    | 23 | 15k  |
| D9DMC<br>02FC02<br>01 | 1/8 M-NPT F-NPT 1/8 15k 316D  | 1/8    | 1/8    | 4.8 | 5/8   16    | 25 | 15k  |
| D9DMC<br>02FC06<br>01 | 1/8 M-NPT F-NPT 3/8 15k 316D  | 1/8    | 3/8    | 4.8 | 1   26      | 31 | 15k  |
| D9DMC<br>04FC01<br>01 | 1/4 M-NPT F-NPT 1/16 15k 316D | 1/4    | 1/16   | 4   | 5/8   16    | 28 | 15k  |
| D9DMC<br>04FC02<br>01 | 1/4 M-NPT F-NPT 1/8 15k 316D  | 1/4    | 1/8    | 6   | 5/8   16    | 30 | 15k  |
| D9DMC<br>04FC04<br>01 | 1/4 M-NPT F-NPT 1/4 15k 316D  | 1/4    | 1/4    | 6   | 3/4   19    | 33 | 15k  |
| D9DMC<br>04FC06<br>01 | 1/4 M-NPT F-NPT 3/8 15k 316D  | 1/4    | 3/8    | 6   | 1   26      | 36 | 15k  |
| D9DMC<br>04FC08<br>01 | 1/4 M-NPT F-NPT 1/2 15k 316D  | 1/4    | 1/2    | 6   | 1+3/16   30 | 41 | 15k  |
| D9CMC<br>04FC12<br>01 | 1/4 M-NPT F-NPT 3/4 10k 316D  | 1/4    | 3/4    | 6   | 1+3/8   35  | 41 | 10k  |
| D9DMC<br>06FC01<br>01 | 3/8 M-NPT F-NPT 1/16 15k 316D | 3/8    | 1/16   | 4   | 3/4   19    | 29 | 15k  |
| D9DMC<br>06FC02<br>01 | 3/8 M-NPT F-NPT 1/8 15k 316D  | 3/8    | 1/8    | 6   | 3/4   19    | 31 | 15k  |
| D9DMC<br>06FC04<br>01 | 3/8 M-NPT F-NPT 1/4 15k 316D  | 3/8    | 1/4    | 7.5 | 3/4   19    | 34 | 15k  |
| D9DMC<br>06FC06<br>01 | 3/8 M-NPT F-NPT 3/8 15k 316D  | 3/8    | 3/8    | 7.5 | 1   26      | 37 | 15k  |
| D9DMC<br>06FC08<br>01 | 3/8 M-NPT F-NPT 1/2 15k 316D  | 3/8    | 1/2    | 7.5 | 1+3/16   30 | 42 | 15k  |
| D9CMC<br>06FC12<br>01 | 3/8 M-NPT F-NPT 3/4 10k 316D  | 3/8    | 3/4    | 7.5 | 1+3/8   35  | 42 | 10k  |
| D9CMC<br>06FC16<br>01 | 3/8 M-NPT F-NPT 1 10k 316D    | 3/8    | 1.00   | 7.5 | 1+3/4   45  | 48 | 10k  |
| D9DMC<br>08FC01<br>01 | 1/2 M-NPT F-NPT 1/16 15k 316D | 1/2    | 1/16   | 4   | 1   26      | 34 | 15k  |
| D9DMC<br>08FC02<br>01 | 1/2 M-NPT F-NPT 1/8 15k 316D  | 1/2    | 1/8    | 6   | 1   26      | 35 | 15k  |
| D9DMC<br>08FC04<br>01 | 1/2 M-NPT F-NPT 1/4 15k 316D  | 1/2    | 1/4    | 8   | 1   26      | 38 | 15k  |
| D9DMC<br>08FC06<br>01 | 1/2 M-NPT F-NPT 3/8 15k 316D  | 1/2    | 3/8    | 9.5 | 1   26      | 41 | 15k  |
| D9DMC<br>08FC08<br>01 | 1/2 M-NPT F-NPT 1/2 15k 316D  | 1/2    | 1/2    | 9.5 | 1+3/16   30 | 46 | 15k  |
| D9CMC<br>08FC12<br>01 | 1/2 M-NPT F-NPT 3/4 10k 316D  | 1/2    | 3/4    | 9.5 | 1+3/8   35  | 46 | 10k  |
| D9CMC<br>08FC16<br>01 | 1/2 M-NPT F-NPT 1 10k 316D    | 1/2    | 1.00   | 9.5 | 1+3/4   45  | 52 | 10k  |
| D9CMC                 | 3/4 M-NPT F-NPT 1/4 10k 316D  | 3/4    | 1/4    | 8   | 1+3/16   30 | 39 | 10k  |

|                       |                              |      |      |    |             |    |      |  |
|-----------------------|------------------------------|------|------|----|-------------|----|------|--|
| 12FC04<br>01          |                              |      |      |    |             |    |      |  |
| D9CMC<br>12FC06<br>01 | 3/4 M-NPT F-NPT 3/8 10k 316D | 3/4  | 3/8  | 12 | 1+3/16   30 | 42 | 10k  |  |
| D9CMC<br>12FC08<br>01 | 3/4 M-NPT F-NPT 1/2 10k 316D | 3/4  | 1/2  | 15 | 1+3/16   30 | 47 | 10k  |  |
| D9CMC<br>12FC120<br>1 | 3/4 M-NPT F-NPT 3/4 10k 316D | 3/4  | 3/4  | 15 | 1+3/8   35  | 47 | 10k  |  |
| D9CMC<br>12FC160<br>1 | 3/4 M-NPT F-NPT 1 10k 316D   | 3/4  | 1.00 | 15 | 1+3/4   45  | 53 | 10k  |  |
| D9CMC<br>16FC04<br>01 | 1 M-NPT F-NPT 1/4 10k 316D   | 1.00 | 1/4  | 8  | 1+1/2   38  | 43 | 10k  |  |
| D9CMC<br>16FC06<br>01 | 1 M-NPT F-NPT 3/8 10k 316D   | 1.00 | 3/8  | 12 | 1+1/2   38  | 46 | 10k  |  |
| D9CMC<br>16FC08<br>01 | 1 M-NPT F-NPT 1/2 10k 316D   | 1.00 | 1/2  | 15 | 1+1/2   38  | 51 | 10k  |  |
| D9CMC<br>16FC120<br>1 | 1 M-NPT F-NPT 3/4 10k 316D   | 1.00 | 3/4  | 19 | 1+1/2   38  | 51 | 10k  |  |
| D9KMC<br>32FC160<br>1 | 2 M-NPT F-NPT 1 7,5k 316D    | 2.00 | 1.00 | 25 | 2+1/2   64  | 59 | 7,5k |  |

*Dimensions and values shown may be changed without prior notice to improve product performances and reliability.  
 Transfer Oil S.p.A. assumes no liability on mistakes nor errors appearing in this spec sheet.  
 Document date: 26/05/2026  
 www.transferoil.com*